

**ELECTRO CIRKEL**

> RETAIL B.V.

S I N C E 1 9 7 0



DIMMER TEST REPORT

Subject Dimmer test report according to WI 60.5.6
Operator ECC QC Team
Number of tested light sources 1 - 5

Product code 2101002900
Brandname Calex
Product description Calex LED Rondo Amber Single spiral filament 220-240V 4W 240lm 2000K E27 dimmable via LED dimmer

Test results:

The following dimmers, commonly used within the E.U., passed our internal dimmer test according to W.I. 60.5.6 and are compatible with the tested light source, as required by Annex V, article 3 (c) of Directive (EU) 2019/2015.

Brand	Type	Min. load	Max. load	Result	Remarks
Busch-Jaeger	2250 U	0	600	PASSED	Noise
Busch-Jaeger	2247 U	0	500	PASSED	Noise, * 1
Jung	244 EX	60	400	PASSED	-
Jung	266 GDE	60	600	PASSED	-
Gira	1182 00 / I01	20	360	PASSED	-
Gira	2262 00	6	100	PASSED	* 1
Peha	431 HAN LED	20	315	PASSED	-
Berker	286710	20	360	PASSED	-
Berker	286610	20	500	PASSED	-
ECO DIM 01	Dim.01	0	150	PASSED	-
ECO DIM 02	Dim.02	0	150	PASSED	-
ECO DIM 03	Dim.03	0	450	PASSED	-
Tradim	2490HP	5	150	PASSED	* 1
Eco Bright	42100003	5	150	PASSED	-
Ehmann	T39.07.1	3	35	PASSED	-
Callex RC Dimmer	176372/2483HC	3	70	PASSED	-
Callex Duo RC Dimmer	176382	3	45	PASSED	-
Peha (Honeywell)	H432-2 LED	6	50	PASSED	-
Lexman Epure		4	200	PASSED	-
Legrand Dooxie	CXM14	3	75	PASSED	-
Schneider	SBD200 LED	5	40	PASSED	-
V-PRO	MJP120	0	120	PASSED	-
Callex Digital Cord dimmer	176386	3	18	PASSED	-

* 1 = Best performance using > 3 light sources

Visitors/Postal address

Lyonstraat 29
3047 AJ Rotterdam
The Netherlands

Contacts

Tel.: +31 (0)10 29819 80
Fax: +31 (0)10 43799 10
info@electrocirkel.com
www.electrocirkel.com

Billings

ING Bank
Rotterdam, The Netherlands
IBAN: EURO NL43 INGB 0007 6924 06
USD NL72 INGB 0020 1190 46
BIC: INGBNL2A

Customs

VAT no.: NL856745741B01

Chamber of Commerce

Rotterdam No. 66895332

CALEX
HOLLAND